



AAP 8000E3





Frequency	Hz	50
Model	AAP 8000E3	


SPECIFICATIONS


- 


Fuel gauge
Fuel gauge is on the fuel tank
- 


OHV
Over Head Valve easy to maintenance
- 


Oil level alarm
When the oil level is low that the engine will not start.
- 


AVR
AVR is a device often solid state, for controlling the output voltage of a generator.
- 


Maintenance free battery
It is long life
- 


Wheel kit
Easy Transportation
- 

Circuit Protector
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.
- 

Generator set out put sockets
- 

Voltmeter
It is a gauge for out put voltage of generator set.
- 

Choke System
When the cold weather, choke system aid to operate the engine
- 

Dual Element air filter
- 

Large capacity fuel tank
15-25 L

AAP 8000E3

GENERATING SET

AC Rated Power	kW	6,00
	kVA	7,50
Maximum Power	kW	6,50
	kVA	8,00
AC Rated Current	AC Rated Current	11,00
DC Rated Current	AC Rated Current	8,00
Voltage	V	400
Frequency	Hz	50
Phase		3
Power Factor		1,00
Fuel Consumption	L/h.	2,50
Run Time	Hour	8,00
Noise Level	dB(A)	76,00

ENGINE

Speed	rpm	3600
Power	Hp	15,0
Cylinder No.		1,0
Cylinder Bulk	mL.	419
Fuel Type		Gasoline
Oil Capacity	L	1,1
Fuel Tank Capacity	L	30,0
Start Type		Electrical

DIMENSIONS

Width	mm.	810
Lenght	mm.	540
Height	mm.	575
Dry Weight	kg.	98,0