

55D!%\$\$\$



Frequency	Hz	50
Model	55D!%\$\$\$	

SPECIFICATIONS



OHV OHV
Over Head Valve easy to maintenance



Oil level alarm
When the oil level is low that the engine will not start.



AVR AVR
AVR is a device often solid state, for controlling the output voltage of a generator.



Circuit Protector
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



Choke System
When the cold weather, choke system aid to operate the engine

55D!%\$\$\$

● GENERATING SET

AC Rated Power	kW	0,85
Maximum Power	kW	0,95
AC Rated Current	AC Rated Current	3,90
DC Rated Current	AC Rated Current	6,00
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h.	0,66
Run Time	Hour	5,00
Noise Level	dB(A)	64,00

● ENGINE

Speed	rpm	3000
Cylinder No.		1,0
Cylinder Bulk	mL.	55
Fuel Type		Gasoline
Oil Capacity	L	0,4
Fuel Tank Capacity	L	2,1
Start Type		Rope

● DIMENSIONS

Width	mm.	460
Lenght	mm.	250
Height	mm.	400
Dry Weight	kg.	15,0