


AAP 1200


ACTIVE POWER





Frequency	Hz	50
Model	AAP 1200	


SPECIFICATIONS


- 


Fuel gauge
Fuel gauge is on the fuel tank
- 


OHV
Over Head Valve easy to maintenance
- 

Oil level alarm
When the oil level is low that the engine will not start.
- 

AVR
AVR is a device often solid state, for controlling the output voltage of a generator.
- 

Circuit Protector
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.
- 

Voltmeter
It is a gauge for out put voltage of generator set.
- 

Choke System
When the cold weather, choke system aid to operate the engine
- 

Dual Element air filter

AAP 1200



● GENERATING SET

AC Rated Power	kW	0,90
Maximum Power	kW	1,00
AC Rated Current	AC Rated Current	3,40
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		1,00
Fuel Consumption	L/h.	0,50
Noise Level	dB(A)	66,00

● ENGINE

Speed	rpm	3000
Fuel Type		Gasoline
Oil Capacity	L	0,4
Fuel Tank Capacity	L	7,0
Start Type		Rope

● DIMENSIONS

Width	mm.	355
Lenght	mm.	465
Height	mm.	385
Dry Weight	kg.	26,0