



55D'&\$\$\$






Frequency	Hz	50
Model		55D'&\$\$\$


● SPECIFICATIONS

-  **OHV** OHV
Over Head Valve easy to maintenance

 **Oil level alarm**
When the oil level is low that the engine will not start.

 **AVR** AVR
AVR is a device often solid state, for controlling the output voltage of a generator.
-  **Circuit Protector**
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.

 **Voltmeter**
It is a gauge for out put voltage of generator set.

 **Choke System**
When the cold weather, choke system aid to operate the engine

55D'&\$\$\$

GENERATING SET

AC Rated Power	kW	1,70
	kVA	2,00
Maximum Power	kW	1,90
	kVA	2,30
AC Rated Current	AC Rated Current	7,70
DC Rated Current	AC Rated Current	6,00
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h.	1,10
Run Time	Hour	5,00
Noise Level	dB(A)	64,00

ENGINE

Speed	rpm	3600
Cylinder No.		1,0
Fuel Type		Gasoline
Oil Capacity	L	0,4
Fuel Tank Capacity	L	3,2
Start Type		Rope

DIMENSIONS

Width	mm.	550
Lenght	mm.	305
Height	mm.	460
Dry Weight	kg.	24,3