



AAP 5500





Frequency	Hz	50
Model	AAP 5500	


SPECIFICATIONS


- 


Fuel gauge
Fuel gauge is on the fuel tank
- 


OHV
Over Head Valve easy to maintenance
- 


Oil level alarm
When the oil level is low that the engine will not start.
- 


AVR
AVR is a device often solid state, for controlling the output voltage of a generator.
- 

Wheel kit
Easy Transportation
- 

Circuit Protector
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.
- 

Voltmeter
It is a gauge for out put voltage of generator set.
- 

Choke System
When the cold weather, choke system aid to operate the engine
- 

Dual Element air filter
- 

Large capacity fuel tank
15-25 L

AAP 5500

● GENERATING SET

AC Rated Power	kW	4,00
	kVA	5,00
Maximum Power	kW	4,50
	kVA	5,50
AC Rated Current	AC Rated Current	17,30
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h.	2,50
Run Time	Hour	10,00
Noise Level	dB(A)	72,00

● ENGINE

Speed	rpm	3600
Power	Hp	11,0
Cylinder No.		1,0
Cylinder Bulk	mL.	337
Fuel Type		Gasoline
Oil Capacity	L	1,1
Fuel Tank Capacity	L	25,0
Start Type		Rope

● DIMENSIONS

Width	mm.	695
Lenght	mm.	555
Height	mm.	580
Dry Weight	kg.	78,0