



# AAP 8000E





Frequency	Hz	50
Model	AAP 8000E	


## SPECIFICATIONS


- 


**Fuel gauge**  
Fuel gauge is on the fuel tank
- 


**OHV**  
Over Head Valve easy to maintenance
- 


**Oil level alarm**  
When the oil level is low that the engine will not start.
- 


**AVR**  
AVR is a device often solid state, for controlling the output voltage of a generator.
- 


**Maintenance free battery**  
It is long life
- 


**Wheel kit**  
Easy Transportation
- 

**Circuit Protector**  
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.
- 

**Generator set out put sockets**
- 

**Voltmeter**  
It is a gauge for out put voltage of generator set.
- 

**Choke System**  
When the cold weather, choke system aid to operate the engine
- 

**Dual Element air filter**
- 

**Large capacity fuel tank**  
15-25 L

# AAP 8000E

## GENERATING SET

AC Rated Power	kW	6,00
	kVA	7,50
Maximum Power	kW	6,50
	kVA	8,00
AC Rated Current	AC Rated Current	26,00
DC Rated Current	AC Rated Current	8,00
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h.	3,00
Run Time	Hour	8,00
Noise Level	dB(A)	76,00

## ENGINE

Speed	rpm	3600
Power	Hp	15,0
Cylinder No.		1,0
Cylinder Bulk	mL.	419
Fuel Type		Gasoline
Oil Capacity	L	1,1
Fuel Tank Capacity	L	30,0
Start Type		Electrical

## DIMENSIONS

Width	mm.	810
Lenght	mm.	540
Height	mm.	575
Dry Weight	kg.	98,0