



# AB 110 ME





Frequency	Hz	50
Model	AB 110 ME	


## SPECIFICATIONS


- 


**Fuel gauge**  
Fuel gauge is on the fuel tank
- 


**OHV**  
Over Head Valve easy to maintenance
- 


**Oil level alarm**  
When the oil level is low that the engine will not start.
- 


**AVR**  
AVR is a device often solid state, for controlling the output voltage of a generator.
- 


**Maintenance free battery**  
It is long life
- 

**Wheel kit**  
Easy Transportation
- 

**Circuit Protector**  
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.
- 

**Generator set out put sockets**
- 

**Voltmeter**  
It is a gauge for out put voltage of generator set.
- 

**Dual Element air filter**
- 

**Large capacity fuel tank**  
15-25 L

# AB 110 ME

## GENERATING SET

AC Rated Power	kW	8,00
Maximum Power	kW	8,80
AC Rated Current	AC Rated Current	34,80
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h.	5,00
Run Time	Hour	3,00
Noise Level	dB(A)	75,00

## ENGINE

Speed	rpm	3000
Power	Hp	18,0
Cylinder No.		2,0
Cylinder Bulk	mL.	570
Fuel Type		Gasoline
Fuel Tank Capacity	L	16,0
Start Type		Electrical

## DIMENSIONS

Width	mm.	740
Lenght	mm.	910
Height	mm.	750
Dry Weight	kg.	122,0