

# AC 66

Engine : Cummins  
 Alternator : Mecc Alte  
 Control System : P 602



## ISO8528

This generator set has been designed to meet ISO 8528 regulation.

## SZUTEST

This generator set is manufactured in facilities certified to ISO 9001.



This generator set is available with CE certification.

## 2000/14/EC

Enclosed product is tested EU noise legislation 2000/14/EC

### 3 Phase Ratings, 50 Hz, PF 0,8

Voltage	Standby Rating (ESP)		Prime Rating (PRP)		
	kVA	kW	kVA	kW	Amp
400/230	66,00	53,00	60,00	48,00	86,00

**Standby Rating (ESP):** Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528. Overload is not allowed.

**Prime Rating (PRP):** Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528. 10 % overload capability is available for a period of 1 hour within 12-hour period of operation, in accordance with ISO 3046.

### OPTIONAL EQUIPMENTS

#### ENGINE

- Fuel-Water Separator Filter
- Low water level alarm
- Oil heater

#### ALTERNATOR

- Anti-Condensation Heater
- Over sized alternator
- Main line circuit breaker

#### CONTROL SYSTEM

- Remote annunciator panel
- Earth fault, single set
- Charge Ammeter

#### OTHER ACCESSORIES

- Automatic or manual fuel filling system
- Manual oil drain pump
- Low and high fuel level alarm
- Residential silencer
- Enclosure: weather protective or sound attenuated
- Duct adapter ( on radiator)
- Inlet and outlet motorised louvers
- Inlet and outlet acoustic baffles
- Trailer
- Tool kit for maintenance
- 1500/3000 hours maintenance kit
- Double wall chassis
- Supplied with oil and coolant - 30 °C
- Battery isolating switch
- Main Fuel Tank

#### TRANSFER SWITCH

- Three Pole Contactor
- Four Pole Contactor

# AC 66

Engine : Cummins  
 Alternator : Mecc Alte  
 Control System : P 602

## ● DIESEL ENGINE SPECIFICATIONS

Manufacturer		Cummins		
Model		S3,8-G7		
No. of Cylinders and Build		4 Cylinder, In Line		
Aspiration and Cooling		Turbo Charged and After Cooled		
Maximum Standby Power		1500 rpm		
		65 kW[87HP]		
Total Displacement	L	3,80		
Bore and Stroke	mm	97 x 128		
Compression Ratio		17,5:1		
Rated Speed (rpm)	rpm	1500		
Governor		Mechanical		
Oil Capacity	L	11,00		
Coolant Capacity	L	19,00		
Intake Air Flow	m <sup>3</sup> /min.	4,60		
Radiator Cooling Air	m <sup>3</sup> /min.	116		
Exhaust Gas Flow	m <sup>3</sup> /min.	10,00		
Exhaust Gas Temperatures	° C	510		
Start System		12 V d.c.		
Fuel Consumption	Load	%100	%75	%50
	L/h	14,70	11,00	6,10

## ● ALTERNATOR SPECIFICATIONS

Make		Mecc Alte
Model		ECO 32-2L/4
Frequency	Hz	50
Power	kVA	60
Design		Brushless, 4 poles
Cos Phi		0,80
Phase		3
Voltage	V	400/230
Current	A	86
Insulation Class		H
Temperatur		H
Stator		2 / 3 steps
Rotor		Single Bearing System, Flexible Disc
Excitation System		Electronic ( AVR )

## ● DIEMENSIONS AND WEIGHT

Open Type	Dry Weight	Lenght	Width	Height	Tank Capacity
	kg.	mm.	mm.	mm.	L
AC 66	950	2150	1050	1450	240
Sound Attenuated Type	Dry Weight	Lenght	Width	Height	Tank Capacity
	kg.	mm.	mm.	mm.	L
AK 40	1300	3100	1110	1750	240

# AC 66

Engine : Cummins  
 Alternator : Mecc Alte  
 Control System : P 602

## 1 P 602 - Control System



- 1 A U]b'gHh g'X]gd'Um'
- 2 8]gd'UmgVc''Vi Hrcb''
- 3 DU[ Yf]bZcfa U]jcbE'Vi Hrcb''
- 4 7 ca a cb U'Ufa ]bX]W]rcf''
- 5 GHh g'@98fj''
- 6 C dYfU]jcb'gY'YV]b[ 'Vi Hrcbg''

## 2 Devices

8G9ža cXY''\$\$'5i hc'A U]bg:] U]i fy Vëbfc''a cXi 'Y''  
 6UHYfmVUf[ Yf]jodi h%, !&\* ( 'j c'hžci rdi h''&+ž' 'j ) '5'f&( 'j E'cf%' ž 'j c'h) 5'f&& ž  
 9a Yf[ YbVhrcd' di g\ 'Vi Hrcb'UbX ž gYg Zc'fVëbfc''V]fV ]rg''

## 3 Construction and Finish

7 ca dcbYbrj ]ogfU''YX' ]b'g\YYgh''Y'YbWcgi fy''D\cgd\UHY'WYa ]W'ždfY!VëU]b[ 'cZghY''dfcj ]XYg Vëffcg]cb  
 fYg]ghUbhgi fZUW''Dc'mYghY'Vëa dcm]Y' dck XYf'rcdVëU]hZcfa g\]] [ 'cgg'UbX'Yi HfYa Y'mXi fUY'Y ž]b]g\''@cV]UV'Y  
 UbX\]b[ YX'dUbY'Xccf' dfcj ]XYg YUgmUWV'gg'hc''Vëa dcbYbrj''

## 4 Installation

7 cblfc' dUbY''jg'a ci bHY'cb VUgYZUa Y'k ]h' ghY''ghUbX''@cW]HY'Uhi'Y'f[ \hig]XY'cZ'HY [ YbYfUrcf'gYhfK \Yb'mci  
 'cc\_'Uhi'Y'; Yb''GYH'Zca '5'HYfbUrcfE

## 5 Generating Set Control Unit

H'Y''8G9''\$\$'jg'U'ghUbXUfX Vëbfc''a cXi 'Y'Zc'ci f[ YbYfUrcf'gYhg'i d'hc'&\$\$\_j 5'UbX'ih\Uj Y'VYYb'XYg][ bYX'hc  
 ghUfhUbX'ghcd'X]YgY'UbX'[ Ug[ YbYfUrcf'gYhg''H'Y'8G9''\$\$'a cXi 'Y'Ug'VYYb'XYg][ bYX'hc'a cb]rcf[ YbYfUrcf  
 ZYei YbVhžj c'tz'W'fYbHžYb[ ]bY'c]'dfYggi fYžVëc'UbhiYa dYfUhi fy'fi bb]b[ \ci fg'UbX'VUHY'fmj'c'lg''A cXi 'Y  
 a cb]rcf'g'h'Y'a U]bg'gi dd'mUbX'gk ]H'W'c] Yf'hc'h'Y' [ YbYfUrcf'k \Yb'h'Y'a U]bg'dck Yf'ZU]g''H'Y'8G9''\$\$'U'gc  
 ]bX]W]HY'g'cdYfU]jcbU'ghUhi g'UbX'ZU'i h'VëbX]j]cbgž'5i hca U]W'mg\i H]b[ 'Xck b'h'Y'; Yb''GYhUbX'[ ] ]b[ 'Hf'Y'Zfghi d  
 ZU'i h'VëbX]j]cb'cZ; Yb''GYhZU]i fy''H'Y'@78'X]gd'Um]bX]W]HY'g'h'Y'ZU'i 'H'

### Standard Specifications

A ]VëcdfcW'ggcf'Vëbfc''YX''  
 @78'X]gd'Uma U\_Yg ]bZcfa U]jcb'YUgmhc'fYUX''  
 (!'j]bYž\*( '1%'&d] ]Y'X]gd'Um'

5i hca U]W'mifUbgZ'fg'VYk'YYb'a U]bg'fi H]h'hc'UbX' [ YbYfUrcf'dck Yf''  
 A Ubi U'dfc[ fUa a ]b[ 'cb'ZcbhdUbY''  
 I gYf]Z]YbX'mgYHi d'UbX'Vi Hrcb''Unci H'  
 : fcbhdUbY'dfc[ fUa a ]b[ ''  
 FYa cHY'ghUff'

9j Ybh'c[ [ ]b[ 'f]g'g'ck ]b[ 'XUHY'UbX'h'a Y''  
 7 cblfc'g' Ghcd#F'YgYhZ'Ubi U'ž5i hcžHYghZ'GHUfz'Vi Hrcbg''5b'UXX]j]cbU'di g\ 'Vi Hrcb'bYi hrc'h'Y'@78'X]gd'Um]g  
 i gYX'hc'gVc''h'fci [ \h'Y'a cXi 'Yg'f'a YH'f]b[ 'X]gd'Umg''

# AC 66

Engine : Cummins  
 Alternator : Mecc Alte  
 Control System : P 602

## Instruments

9B: #9  
 9b[ ]bY'gdYYX"  
 C]'dfYggi fY"  
 7cc'UbhY'a dYfUhi fY"  
 F i b' hja Y"  
 6UHYfmj c'rg"  
 7cbZ[ i fUVY' hja ]b[ "  
 ; 9B9F 5HCF  
 J c' hU[ Y f@ @B' "  
 7i ffYbhf@ @& @' "  
 : fYei YbVW"  
 A 5-BG  
 J c' hU[ Y f@ @B' "  
 : fYei YbVW"  
 A U]bg'fYUXn'  
 A U]bg'YbUV'YX"  
 ; Yb"GYhfYUXn'  
 ; Yb"GYhYbUV'YX"

## Protection Circuits

K 5F B-B;  
 7\Uf[ Y Z]i fY"  
 6UHYfm@ck #:[ \ ] c' hU[ Y"  
 : U] 'hc' ghd"  
 @ck #:[ \ ] [ YbYfUhc'f'j c' hU[ Y"  
 I bXYf#j Yf[ YbYfUhc'f'Z'Yei YbVW"  
 Cj Yf# bXYf'gdYYX"  
 @ck c]'dfYggi fY"  
 <][ \ V'c'UbhY'a dYfUhi fY"  
 G<I H8CK BG  
 : U] 'hc' gUff"  
 9a Yf[ YbVW'ghcd"  
 @ck c]'dfYggi fY"  
 <][ \ V'c'UbhY'a dYfUhi fY"  
 Cj Yf# bXYf'gdYYX"  
 I bXYf#j Yf[ YbYfUhc'f'Z'Yei YbVW"  
 I bXYf#j Yf[ YbYfUhc'f'j c' hU[ Y"  
 C]'dfYggi fY'gYbgcf'cdYb"  
 7cc'UbhY'a dYfUhi fY'gYbgcf'cdYb"  
 9@97 HF =75@HF -D  
 ; YbYfUhc'f'c'j YfW'ffYbH'

## Options

: 'YI J'V'Y'gYbgcf'WVb VY V'c'bfcc'YX'k ]h' h'Ya dYfUhi fYz  
 dfYggi fYz dYfVW'bH[U' Y f'k Ufb]b[ #]i h'Xck b# 'YVW'VW' h'f'dL  
 @c'W'gYh]b[ 'dUfUa YH'fg'UbX'a cb]h'f]b[ 'Z'ca 'D7' hc  
 V'c'bfcc' a cXi 'Y'k ]h' I G6 V'c'bbYVW'cb'fa Ul '\* 'a H'

## Standards

9'YVW'VW' GUZYhm#9A 7 'V'a dUfV']hm6G'9B '\* \$- ) \$  
 9'YVW'VW' Vi g]bYgg'Yei ]da YbH'  
 6G'9B '\*%\$ \$! \*! & 9A 7 'ja a i b]mighUbxUfX"  
 6G'9B '\*%\$ \$! \*! ( '9A 7 'Ya ]gg]cb'ghUbxUfX"

## Static Battery Charger

'6UHYfmVUf[ Yf ]g'a Ubi ZVW' fYX'k ]h' gk ]h'W]b[ !a cXY'UbX'GA 8 'YVW'bc'c[ mUbX'ih\Ug\ ] [ \ YZ]VbYVW' 6UHYfmVUf[ Yf  
 a cXY'gfci hdi hJ !=VUfUW'f]gh]W]g'j YfmV'cgY'hc'gei UfY'UbX'ci hdi h]g' ]'Ua dYfz% z' ]'Z'f'& j'c'hUbX'&+Z' ]'Z'f'& ( ' ]'  
 #bdi h% , ' ! & \* ( j c'h57 "' Dfc' ]bY' & ( \$ ) \Ug'Z' "mici hdi hg\chV'VW ]hdfchV'W]cb'UbX'ihVWb VY i gYX'Ug'U'VW'ffYbhgci fVW"  
 Dfc' ]bY' %&\$ ) #& ( \$ ) VUf[ Yf\Ug\ ] [ \ YZ]VbYVW'cb[ " ]Z'Z' "ck ZU]i fY'fUfYz' ] [ \ hk Y] [ \ hUbX' "ck \ YUhfUX]UfYX' ]b  
 UVW'cfXUbW'k ]h' " ]bYUf'U'fYfbU]j Yg' H\Y'VUf[ Yf ]g'Z'hYX'k ]h' U'dfchV'W]cb'X]cXY'UV'cgg'h'Y'ci hdi h'7 cbbYVW'VUf[ Y'Z]  
 fY'UmV'c' ]'VYh'YYb'dcg]h]j Y'ci hdi hUbX'7: 'ci hdi h' H\Y'mUfY'Yei ]ddYX'k ]h' F: =Z]h'f'hc'fYXi V'Y'YVW'VW'bc]gY'fUX]UfYX'  
 Z'ca 'h'Y'XY'jVW"; Uj Ub]W' m]gc'UfYX' ]bdi hUbX'ci hdi h]hd]VW' m( \_J 'Z'f'\ ] [ \ fY' ]UV' ]h'f'

# AC 66

Engine : Cummins  
 Alternator : Mecc Alte  
 Control System : P 602

## AK 40 - Canopy



- 1 Steel structures
- 2 Emergency stop push button
- 3 Control panel is right side of the set.
- 4 Corrosion-resistant locks and hinges
- 5 Sump drains valves
- 6 Sound proof foam material
- 7 Lifting Points

## Introduction

Sound-attenuated and Weather-protective Enclosures Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet event the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies (10- 300kVA) provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

## Standard Specifications

Compact footprint, low profile design.

Enclosure, generator set, exhaust system and fuel tank are pre-assembled, pre-integrated and shipped as one package

Body made from steel components treated with polyester powder coating

Fire retardant foam insulation

Easy access to all service points

Exhaust system inside canopy

Large doors on each side

Control panel viewing window in a lockable access door

Emergency stop push button mounted on enclosure exterior

Cooling fan and battery charging alternator fully guarded

Fuel fill and battery can only be reached via lockable access doors.

Lifting points on the top of canopy and base frame

Customer options available to meet your applications needs.

Aksa makes its generating sets' noise level tests in accordance with directive 2000/14/EC validation of the noise level test has been approved by the notified body Szutest

Width	mm.	1110
Lenght	mm.	3100
Height	mm.	1750
Fuel Tank Capacity		240